HXLIGHTING™

X8™ Line-Voltage Tube

Safe, high-efficiency replacements for fluorescent tubes in:

- Offices
- Showrooms
- Warehouses and storage facilities
- Retail locations
- Schools
- Refrigerated storage areas
- Outdoor/vapor-proof fixtures
- Anywhere T8 fluorescent tubes are used





LX88LV400 Single-pin




LX88LV400 HO (RDC)



LX84 / LX82

Features

- **X**treme**8** Line-voltage dual-end design – Type B
- Eliminates high-maintenance fluorescent ballasts
- Built-in ASIC Safety Switch eliminates shock risk during installation
- Frosted glass tube will not sag or yellow - no pixelation - Excellent heat dissipation
- Exceptional light quality – 300 degree dispersion – Low glare
- Instant on at full brightness – no warm-up time
- High-Efficiency **HX Driver**™ - 120-277 volt
- Extreme Performance – 50,000+ User Hours
- Earth-friendly design contains no mercury or lead.
- **EcoHX PLUS**™, Outdoor, Cool and Natural color tones



Watts	Length	Product Code	Description	Color Tone	CRI	Lumens	Case Qty.
40W	8ft.	**LX88LV400**	LED/X8/8FT/120-277V/40W/EcoHXO[1]	Outdoor	85	5500	30/15
17W	4ft.	**LX84LV17EXP**	LED/X8/4FT/120-277V/17W/EcoHX PLUS	EcoHX PLUS	90+	2500	36
17W	4ft.	**LX84LV17EXP-G**	LED/X8/4FT/120-277V/17W/EcoHX PLUS-G[2]	EcoHX PLUS	90+	2500	36
25W	4ft.	**LX84LV25EXP**	LED/X8/4FT/120-277V/25W/EcoHX PLUS	EcoHX PLUS	90+	3700	36
17W	4ft.	**LX84LV17C**	LED/X8/4FT/120-277V/17W/EcoHXC	Cool	85	2200	36
17W	4ft.	**LX84LV17N**	LED/X8/4FT/120-277V/17W/EcoHXN	Natural	85	2200	36
12W	3ft.	**LX83LV12EXP**	LED/X8/3FT/120-277V/12W/EcoHX PLUS	EcoHX PLUS	90+	1750	36
12W	3ft.	**LX83LV12C**	LED/X8/3FT/120-277V/12W/EcoHXC	Cool	85	1600	36
12W	3ft.	**LX83LV12N**	LED/X8/3FT/120-277V/12W/EcoHXN	Natural	85	1600	36
9W	2ft.	**LX82LV9EXP**	LED/X8/2FT/120-277V/9W/EcoHX PLUS	EcoHX PLUS	90+	1300	36
9W	2ft.	**LX82LV9C**	LED/X8/2FT/120-277V/9W/EcoHXC	Cool	85	1200	36
9W	2ft.	**LX82LV9N**	LED/X8/2FT/120-277V/9W/EcoHXN	Natural	85	1200	36

[1] When ordering specify ***single-pin*** or ***HO*** (RDC).

[2] **HX-Guard™** coated tubes are NSF certified and USDA approved. **HX-Guard™** coating complies with FDA and OSHA requirements for use in food service and food production facilities.

© 2026 HX Lighting, Inc. - 17 West Main Street - PO Box 149 – Dallastown, PA 17313 – 717-246-9500 – www.HXLightinginc.com

10/2026


Accessories



LD2PI



TSLX8-LR TSLX8-NG



TSLX8-LRS TSLX8-NGS



TSLX8-LRF TSLX8-NGF



TSSPC



TSSP



TSRDCHC



TSRDCH



LS8

Product Code	Description
LD2PI	LUMINAIRE DISCONNECT/PUSH-IN/18-12AWG - (Order 1 per fixture)
TSLX8-LR	TUBE SOCKET/LED/X8 [LINE - RED] - (Order 1 per tube)
TSLX8-NG	TUBE SOCKET/LED/X8 [NEUTRAL - GREEN] - (Order 1 per tube)
TSLX8-LRS	TUBE SOCKET/LED/X8/SHORT [LINE - RED] - (Order 1 per tube)
TSLX8-NGS	TUBE SOCKET/LED/X8/SHORT [NEUTRAL - GREEN] - (Order 1 per tube)
TSLX8-LRF	TUBE SOCKET/LED/X8/FOOT [LINE - RED] - (Order 1 per tube)
TSLX8-NGF	TUBE SOCKET/LED/X8/FOOT [NEUTRAL - GREEN] - (Order 1 per tube)
TSSPC	TUBE SOCKET/SINGLE-PIN/COMPRESS
TSSP	TUBE SOCKET/SINGLE-PIN
TSRDCHC	TUBE SOCKET/RDC/HORIZONTAL/COMPRESS
TSRDCH	TUBE SOCKET/RDC/HORIZONTAL
LS8	LAMP SUPPORT/T8 (mounting screw included)

Exclusive color-coded **Turn-N-Lock Tube Sockets** provide precise and accurate connectivity.

Order one **GREEN** and one **RED** socket per tube. Do not mix standard and short sockets on the same tube.

Luminaire Disconnect allows for easy and safe fixture installation and service. Order one per fixture

Turn-N-Lock Tube Sockets and **Luminaire Disconnect** are available separately or as pre-wired **Retrofit Kits**.

When ordering **Retrofit Kits** you must specify the **type** of fixture and the **number** of fixtures being converted.

Example:

Retrofit qty 9 – 4-tube 2x4 troffer
Retrofit qty 6 – 4-tube 8ft channel
Retrofit qty 6 – 3-tube wraparound

© 2026 HX Lighting, Inc. - 17 West Main Street - PO Box 149 – Dallastown, PA 17313 – 717-246-9500 – www.HXLightinginc.com